

FIDVR

The transient behavior of loads

John Undrill
September 2015

Load modeling issues

Load composition

- lighting
- electronic power supplies
- single phase motors
- three phase motors

Static characteristics (for load flow)

constant P,Q constant I,B constant G,B variations on the theme

Behavior in transients

- stay-on/shutdown
- slow-down/reaccelerate
- run/stall

- discharge and LED lighting
- miscellaneous motors
- residential air conditioners

Asymptotic behavior

- linear dynamics
- mode changes

- control gain and bandwidth
- sensitivity to voltage/frequency conditions

Load modeling issues

Incandescent lighting / resistance heating

Was/is reasonable to treat as algebraic function of voltage/frequency

Discharge and new-technology lighting

We are increasingly concerned that algebraic modeling is reasonable only within narrow voltage/frequency bands

Large rotating machines - generators/motors


We can model large machines very closely but we are often quite lax about modeling the driven loads

General population motor loads

Phasor-level modeling can reveal characteristics in steady operation
but cannot address behavior in the initiating parts of grid transients


Turbine generators



Time scale of 1 - 10 seconds



Industrial motors



Inertia constant $\sim 0.3 \text{ sec} < H < \text{very large}$
Time scale of 0.5 - 10 seconds







Short circuit at terminals of 100KW three phase motor driving a pump -

$H = 0.3$ second





Motor contributes significant short circuit current

Speed dips during fault - reacceleration is decisive



Immediate **negative** peak of torque transient approaches **six times** rated torque

Well understood behavior



Central to circuit breaker rating standards

Voltage dip at terminals of 100KW three phase motor driving a pump -









$H = 0.3$ second

Current contains AC and unidirectional components

Reactive power reverses during voltage dip - motor contributes to support of voltage


Immediate **negative** peak of torque transient approaches **six times** rated torque

Response to alternating torque is observable in speed transient, but only to minimal extent



Air conditioner rotor - approximately 5kW

$H_{\text{motor}} \approx 0.05$ second
Time scale of tenths of a second



Voltage dip at terminals of 5KW single phase motor driving a residential air conditioner








$H = 0.048$ second

Speed is pulled down very strongly by the negative electromagnetic torque


Motor stalls and does not restart

Immediate **negative** peak of torque transient approaches **eight times** rated torque

Current drawn by stalled motor is **five times** normal load current



FIDVR is not only a positive sequence issue



Motor behavior is sensitive to

Supply system impedance





Driven load type and characteristics (torque/speed/angle)

Electrical phase at moment when voltage dip is initiated

Rate of change of voltage in initiation of voltage dip

Presence of other motors and load on feeders

etc.



What **generators and large rotating equipment** will do depends on things that we can model with phasor calculation and positive sequence networks

What **small motors and electronic equipment** will do depends on things that happen much faster than can be seen by models based on phasor calculation

We cannot see what we want with $R + jX$

We could, *perhaps*, see a lot if we could use $R + Ldi/dt$

Even after living through 25 iterations of Moore's law, the computers that I can use are not fast enough or big enough to handle grid-size systems at the di/dt level

When they do become available, the assembly of the required data will be a task of the same scale as we have today

We have to proceed

based on the physical understanding that we have, combined with carefully assembled empirical information

there are practical steps that we should take

End